LASER®

Digital Multimeter CAT III - 600V

This CAT III multi-meter is for measuring both DC and AC voltages, DC current, resistance, diodes and continuity. It features an easy to read digital display with backlight together with a data hold function, continuity buzzer and low battery indicator. Suitable for voltages up to 600V, it's ideal for testing wiring and circuitry in the workshop and at home. The meter has a compact size and is supplied with a PVC cover, with an integral flip down stand for ease of use, together with a pair of test leads.



Additional Information

- Features: Data hold function, diode test, continuity buzzer, low battery indicator, overload protection, backlight & double fuse design (250mA/600V + 10A/600V).
- Size: 31 x 69 x 138mm. Weight: 170g (approx).
- DC voltage: Range; 200mV, 2V, 20V, 200V & 600V. Accuracy; ±0.5% ~ ± 0.5%. AC voltage: Range; 200V & 600V. Accuracy; ±1.2%.
- DC Current: $20\mu\text{A}$, $200\mu\text{A}$, 2mA, 20mA, 200mA & 10A. Accuracy; $\pm 1.0\% \sim \pm 3.0\%$. Resistance: 200Ω , $2k\Omega$, $20k\Omega$, $20k\Omega$, $200k\Omega$, $2M\Omega$. Accuracy; $\pm 0.8\% \sim \pm 1.0\%$.
- Supplied with test leads, PVC cover, manual & 9V battery. CE, UKCA & RoHS compliant. CAT III.

http://lasertools.co.uk/product/8801















